

ROTOFIX 32 A



Inhalt des Dokuments / content of the document

Gebrauchsanweisung (DE)

Operating instructions (EN)

Mode d'emploi (FR)

Istruzioni per l'uso (IT)

Rotoren und Zubehör / Rotors and accessories



NOTICE

Damage to the device electronics due to incorrect voltage or frequency at the device circuit breaker.

- Operate the device with the correct mains voltage and mains frequency.
The value can be found in the technical data and on the rating plate.



NOTICE

Damage to the device and samples due to premature program termination.

Premature program termination is caused by power failure, switching off during the program or pulling out the mains plug.

- Do not switch off the device while the program is running.
- Do not trigger the emergency release on the device while the program is running.
- Do not pull out the mains plug while the program is running.

3 Device overview

3.1 Technical data

Manufacturer	Andreas Hettich GmbH & Co. KG, D-78532 Tuttlingen	
Model	ROTOFIX 32 A	
Type	1206 1206-34	1206-01 1206-33
Mains voltage ($\pm 10\%$)	208-240 V 1~	100-127 V 1~
Mains frequency	50-60 Hz	50-60 Hz
power consumption	300 VA	300 VA
Power consumption	1.4 A	3.0 A
max. capacity	4 x 100 ml / 32 x 15 ml	
max. permissible density	1.2 kg/dm ³	
max. speed (RPM)	6000	
max. acceleration (RCF)	4226	
max. kinetic energy	3160 Nm	